

(818) 254-8590 | hello@sound-secure.com

# SS-705 Microphone



#### Product Features

Weather Resistant Enclosure for Outdoor Applications

Mic Level Audio Signal - No External Power Supply Required

Includes 40 Feet of Cable with a Pre-Terminated 3.5mm Plug for Fast Installation

■ Can be Surface Mounted or Connected with 3/4" Threaded Conduit The SS-705 is an outdoor rated mic level microphone with an omni-directional pickup radius of approximately 12 feet. Housed in a weather resistant enclosure, the SS-705 is suitable for outdoor applications. The SS-705 does not require external power and is compatible with select IP cameras featuring a mic level audio input. The microphone includes 40 feet of cable with a 3.5mm plug. The cable may be threaded through either the top or rear of the enclosure.

## Product Specs

<b>frequency response:</b>	signal to noise ratio:
50Hz - 16kHz	60dB
sensitivity(1m,1w):	output impedance:
-30dB	2.2k Ohms Max
POWER REQUIREMENTS:	DIMENSIONS:
<.5mA @ 1.5VDC	2.8"w 4.6"h 2.2"d
weight:	<b>OPERATING TEMP RANGE:</b>
1 LB	-20C - +60C

SoundSecure recommends reviewing state and local statutues governing the use of audio equipment in security systems and to use audio products in a manner consistent with expectations of privacy.



#### SS-705 Installation Instructions

(818) 254-8590 | hello@sound-secure.com



## **INSTALLATION INSTRUCTIONS**

1. Connect the microphone cable to the IP camera audio input. In the event that the camera's audio input is a terminal block, use a 3.5mm to bare wire adapter (not supplied) or cut the connector and strip the wire. Connect the white wire to ground and the red wire to signal. Do not connect the microphone to 12Vdc power.

2. Ensure that the camera's audio settings are set to "mic in." Most IP cameras' default setting is "line in" which when used with the SS-705 will result in faint or inaudible sound.

Assembled in the USA with Imported Parts